



# **SL-T3010PTB020-L200-R** DATA SHEET

 SPEC. NO.
 :
 SZ21061201

 DATE
 :
 2022/02/16

 REV.
 :
 A/2

Approved By:

Checked By:

Prepared By:

Part No.	SL-T3010PTB020-L200-R	Page	1 of 9
			LG-QR-R009-01

## LIGHT ELECTRONICS CO., LTD.

# LIGHT

# RoHS

## Features

- Pb free product—RoHS compliant
- Low power consumption, High efficiency
- Reliable and rugged
- Long life solid state reliability
- Fast response time
- High photo sensitivity

## Package Dimension







#### Absolute Maximum Ratings at Ta=25℃

Parameter	MAX.	Unit	
Power Dissipation	100		
Collector-Emitter Voltage	30 V		
Emitter-Collector Voltage	5	V	
Collector Current	50	mA	
Moisture Sensitivity Level <sup>*1</sup>	3		
Operating Temperature	-40°C to + 85°C		
Storage Temperature	-40°C to + 85°C		
IR Reflow Temperature <sup>*3</sup>	260℃ for 10 Seconds MAX.		

#### 1. Storage:

(1). Storage requirements before vacuum bag opened: Temperature<30°C, Humidity<65%RH;

- (2). Check air leakage and vacuum bag damage before opened. If there is any issue found, check the humidity indicator card immediately after bag opened:
  - a. If color changes on "10% circle" of the humidity indicator card only and not the circles of 20% and above, components can be used without additional handling;
  - b. If color changes on both 10% and 20% circles but not the circles of 30% and above, components must be dehumidified according to the conditions of bullet (5);
  - c. If color changes on 10%, 20%, and 30% circle or above, the product should be returned to the supplier for high temperature dehumidification;
- (3). After bag opened, manual soldering or reflow process must follow the following requirements:
  - a. Complete soldering / reflow within 168 hours;
  - b. Requirements of working environment: Temperature<30°C, Humidity<60%RH;
- (4). If the working condition is outside (3)a or (3)b requirement, the components must be dehumidified according to the conditions of bullet (5);
- (5). Low temperature dehumidification: temperature  $60\pm5$  °C, 24 hours;
- (6). Shelf life: 1 year. If it's over 1 year from the production date on the package label, the components must be dehumidified according to the condition of bullet (5). If customer is unable to dehumidify, return components to LIGHT for dehumidification.

#### 2. Cleaning:

Use alcohol-based cleaning solvents such as isopropyl alcohol to clean the LED if necessary.

#### 3. IR Reflow Temperature:

It is the Plate Temperature.

4. Caution in ESD:

Static Electricity and surge damages the LED. It is recommend to use a wrist band or anti-electrostatic glove when handling the LED. All devices, equipment and machinery must be properly grounded.

Page 3 of 9





### Electrical Optical Characteristics at Ta=25°C

Parameter	Symbol	Min.	Тур.	Max.	Unit	Test Condition
Collector-Emitter Breakdown Voltage	BV <sub>CEO</sub>	30			V	I <sub>C</sub> =0.1mA Ee=0mW/cm <sup>2</sup>
Emitter-Collector Breakdown Voltage	BV <sub>ECO</sub>	5			V	$I_E=0.1mA$ Ee=0mW/cm <sup>2</sup>
Collector-Emitter Saturation Voltage	V <sub>CE(SAT)</sub>			0.4	v	I <sub>C</sub> =0.1mA Ee=1mW/cm <sup>2</sup>
Rise Time	Tr		15		μs	V <sub>CE</sub> =5V
Fall Time	Tf		15		μs	$R_L=1K\Omega$ $I_C=1mA$
Collector Dark Current	I <sub>CEO</sub>			100	nA	V <sub>CE</sub> =10V Ee=0mW/cm <sup>2</sup>
On State Collector Current	I <sub>C(ON)</sub>	0.8	1.0		mA	$V_{CE}=5V$ Ee=1mW/cm <sup>2</sup> $\lambda p=940$ nm

#### Note:

1.  $\theta_{1/2}$  is the off-axis angle at which the  $I_{C(ON)}$  is half the axial  $I_{C(ON)}.$ 

Part No. SL-T3010PTB020-L200-R	Page	4 of 9
--------------------------------	------	--------

# LIGHT





5 of 9 LG-QR-R009-01

Page



## Ic(on) Bin Code (V<sub>CE</sub>=5V, Ee=1mW/cm<sup>2</sup>, λp=940nm)

BIN CODE	Min. (mA)	Max. (mA)
1	0.8	1.0
2	1.0	1.2
3	1.2	1.44
4	1.44	1.73
5	1.73	2.08

**NOTE**: The Ic(on) guarantee should be added  $\pm 15\%$  tolerance.

		D	( 60
Part No.	SL-T3010PTB020-L200-R	Page	6 of 9



## LIGHT ELECTRONICS CO., LTD.















### Suggest IR Reflow Condition For Lead Free



- 1. Reflow soldering should not be done more than two times.
- 2. When soldering, do not put stress on the LEDs during heating.

### Soldering iron

- 1. When hand soldering, the temperature of the iron must less than  $350^{\circ}$ C for 3 seconds.
- 2. The hand solder should be done only once.

### Repairing

Repair should not be done after the LEDs have been soldered. When repairing is unavoidable, a double-head soldering iron should be used (as below figure). It should be confirmed beforehand whether the characteristics of LEDs will or will not be damaged by repairing.

